

# RA-04

## Integrated Amplifier

Continuous Power Output	(20 – 20kHz, <0.03%, 8 ohms): 40 watts/ch
Total Harmonic Distortion (20Hz-20kHz)	<0.03% at rated power, 1/2 power or 1 watt
Frequency Response	Phono Input: 20Hz – 15kHz: ±0.3dB Line Level Inputs: 10Hz – 40kHz: ±0.1dB
Input Sensitivity / Impedance	Phono Input: 2.5mV / 47kOhms Line Level Inputs: 150mV / 24kOhms
Pre-amp Output / Impedance	1V / 470 Ohms
Tone Controls – Bass / Treble	±6dB at 100Hz / 10kHz
Dimensions (W x H x D) mm	435 x 72 x 342mm
Available Finishes	Silver / Black
12 Volt Trigger	Yes
Remote Control	No
Inputs	Phono, CD, Tuner, Aux 1, Aux 2, Media Player
Loudspeaker Outputs	On / Off A. B. A+B



For great sound, nothing more, nothing less, the RA-04 is reference. It offers identical performance to the RA-05; the only difference is the RA-04 does not include remote control operation. What it does include is Rotel's Balanced Design Concept in practice, in the form of high-performance parts and finely-honed sound.

- Symmetrical circuit board layout
- Short signal path routing
- UK-designed metal film resistors
- US-made super low-noise resistors
- Rotel toroidal transformer and power supply
- Electronic speaker protection
- 12v trigger power control